



# GV-800

DVR CARD เชื่อมต่อกับคอมพิวเตอร์ 16 Channel



BNC



D-Type

## Specifications

|                               |   |
|-------------------------------|---|
| <b>Input Type</b>             | GV-800 BNC: BNC X 4<br>GV-800 D-Type: DB15 X 2            |
| <b>Video Input(s)</b>         | 4, 8, 12, 16 Cams   |
| <b>Audio Input(s)</b>         | 4 Channels  |
| <b>Recording Rate</b>         | At 320 X 240 Resolution<br>120 fps (NTSC), 100 fps (PAL). |
| <b>Display Rate</b>           | 120 fps (NTSC), 100 fps (PAL).                            |
| <b>Video Resolution -</b>     | NTSC/PAL Full D1, Half D1, CIF                            |
| <b>Compression Format</b>     | Geo MPEG4, Geo MPEG4 (ASP), Geo H264, Geo H264 V2         |
| <b>GV-DSP Support</b>         | Yes   |
| <b>GV-A16 Support</b>         | Yes   |
| <b>GV-NET Card Support</b>    | Yes   |
| <b>GV-NET/IO Card Support</b> | Yes   |

|                           |   |
|---------------------------|---|
| <b>Dimensions (W x H)</b> | GV-800 BNC: 144 x 98 ( mm ) / 5.67 x 3.86 (in)<br>GV-800 D-Type: 144 x 98 ( mm ) / 5.67 x 3.86 (in) |
|---------------------------|---|

## Minimum System Requirements

|                     |  |
|---------------------|--|
| <b>OS Supported</b> | Windows 2000 / XP / Windows Server 2003 / Vista<br>(Not support 64-bit version of Windows) |
| <b>CPU</b>          | Pentium 4-2.4GHz with Hyper-threading or above   |
| <b>RAM</b>          | 2 x 512 MB dual channel  |
| <b>HDD</b>          | 80GB (recommended)   |
| <b>VGA</b>          | ATI Radeon 9550 or above    NVIDIA 6200 or above   |
| <b>DirectX</b>      | 9.0 and above  |



The manufacturer reserves the right to change the specification and technical data of device.  
The picture may vary from the real product.